

Standard Transfer Switch

Wall Mount
010-507-10
Rack Mount
010-506-10



Product Description

The Standard Transfer Switch pairs with the EDP double-conversion series and EP line-interactive UPS series. It provides power source selection, generator capabilities, and alarm reporting via dry contact relays. Includes maintenance bypass switch.

Specifications

Parameter	Specification
Output Capacity	2kW
Cooling System	Convection
Operating Temperature	-37°C - + 74°C
Dimensions (W x H x D)	19" x 3.5" x 5.5"

Specifications Cont.

AC Input	Specification
Connections	Terminal Block 4-14AWG
Phase	Single Phase 3-Wire
Voltage	120V Nominal
Frequency	60Hz
Input Power Factor	0.98-1.0
Power Consumption	3W

AC Output	Specification
Output Power Connection	Terminal Blocks 4-14AWG
Phases	Single Phase 3-Wire
Voltage	120V Nominal
Voltage Regulation	Rated Voltage $\pm 5\%$
Current Capacity	16.67A @120VAC
Rated Frequency	60Hz
Voltage Waveform	Sine Wave
Transfer Time	5 Cycles or Less
Load Power Factor	0.7-1.0
Over Current Protection	Upstream Circuit Breaker/ Internal Fuses
Overload Capability	150%

Transfer Relays	Specification
Output Transfer Relay	30A/277VAC

Dry Contact Sense Relays	Specification
Switching Power	60W
Switching Voltage	12VDC
Max Switching Current	5A
Carrying Current	2A

Contact Us

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 440 366 6966 Fax: +1 440 366 6802 Email: engsupport@gomultilink.com	Tel: +1 954 499 9203 Mobile: +1 305 684 2388 Email: hquinones@gomultilink.com



Scan
QR for
website.

Multilink, Inc
580 Ternes Ln
Elyria, OH 44035
Tel: (440) 366-6966
Fax: (440) 366-6802



facebook.com/GoMultilink1



twitter.com/GoMultilink



youtube.com/GoMultilink

Contact Us

North America	Europe, Middle East & Africa	Latin & South America
Tel: +1 440 366 6966	Tel: +1 440 366 6966	Tel: +1 440 366 6966
Fax: +1 440 366 6802	Fax: +1 440 366 6802	Mobile: +1 440 366 6802
Email: engsupport@gomultilink.com	Email: engsupport@gomultilink.com	Email: lasupport@gomultilink.com